

POWERZONE[®] By SENCER

Gasoline Generator



- Compact Structure
- Low Noise
- Easy Maintenance
- Low Fuel Consumption
- Supreme Quality

Model No. PG-2800R PG-4800E PG-7800E PG-8800E PG-9800E

Engine	3.0 HP	7.0 HP	13.0 HP	14.0 HP	16.0 HP
Displacement	98 cc	208 cc	389 cc	420 cc	459 cc
Compression Ratio	8.5 : 1	8.5 : 1	8.0 : 1	8.0 : 1	8.0 : 1
Rated Frequency	50 Hz	50 Hz	50 Hz	50 Hz	50 Hz
Rated Voltage	220 v	220 v	220 v	220 v	220 v
Rated Power	1.0 kW	2.8 kW	5.0 kW	6.5 kW	7.5 kW
Max Power	1.2 kW	3.1 kW	5.5 kW	7.0 kW	8.0 kW
Fuel Tank Capacity	6 L	15 L	25 L	25 L	25 L
Full Load Cont. Running Time	8.0 H	9.5 H	8.5 H	8.5 H	8.0 H
1/2 Load Cont. Running Time	12.5 H	13.5 H	13.5 H	13.0 H	12.5 H
Net Weight	28 kg	45 kg	81 kg	88 kg	94 kg

Model No. PG-13800E (Single Phase) PG-13800ET (Three Phase)

Engine	24.0 HP	24.0 HP
Displacement	688 cc	688 cc
Compression Ratio	8.5 : 1	8.5 : 1
Rated Frequency	50 Hz	50 Hz
Rated Voltage	220 v	380 v
Rated Power	10 kW	10 kW
Max Power	12 kW	12 kW
Fuel Tank Capacity	30 L	30 L
Full Load Cont. Running Time	6.0 H	6.0 H
1/2 Load Cont. Running Time	10.0 H	10.0 H
Net Weight	195 kg	195 kg

